



**Single-phase Automatic Battery Chargers  
Types ABC11 & ABC12  
For charging standby & on-line batteries ABC12  
chargers have filtered outputs  
to 100mv (30mv optional)**

---

## ***GENERAL DESCRIPTION***

---

The ABC-series of float chargers are completely solid state, automatic and of the constant voltage type having:

- AC voltage compensation
- DC voltage regulation
- Full current limit
- Filtered DC output (ABC12)

Two rate charging is standard. A control switch allows selection of float-automatic, or high rate charge. With optional Auto-Charge, in the automatic mode, the charger will high rate charge the battery whenever it is discharged. The charger will raise the voltage to the high rate setting and maintain this level for a timed interval. Recharge of the battery is accomplished without excessive over or under charging.

The ABC-series chargers are fully current limited. If current demands exceeds the chargers rating, the output voltage drops rapidly, protecting the charger and the system to which it is connected. The chargers fuses or breakers will not trip during such overload conditions.

## ***STANDARD FEATURES***

---

Conservative component selection and design assures long life  
LEDs for AC-ON, and high rate charge  
AC and DC surge protection  
Float / high rate control switch  
DC voltmeter & ammeter 2%  
Precise voltage regulation  
Fully current limited  
AC input and DC output fuses  
Reverse battery protection  
Natural convection cooling  
Modular construction



---

## ***OPTIONS***

---

AC and DC 2-pole breakers  
Precision metering  
Extra filter (Use ABC12)  
Battery temperature compensation  
AC failure alarm relay  
Multi-Alarm Monitor includes four alarms & LEDs with common relay High DC volts, Low DC volts, Rectifier failure and Ground fault.  
Separate alarm relays may be specified.  
Auto-Charge Control or manual timers  
Audible alarm  
Drip Shields  
CE compliance and marking  
Many other accessories available

# SPECIFICATIONS

## INPUT

Voltage: 120, 208, 220, 240, 480 or other  
 Phase: Single  
 Frequency: 50 or 60 Hertz

## OUTPUT

Voltage: 12, 24, 32, 48, 120, 240 or other nom.  
 Current: From 3 to 100 amps  
 Regulation: +/- 1/2% from no load to full load,  
 with +/- 10% AC line variation  
 ABC12 types have filtering to 100mv RMS with  
 4X battery connected

## OPERATING TEMPERATURE

From +14°F (-10°C) to +122°F (+50°C)

## ADJUSTMENTS

Internal potentiometers for float, high rate and  
 current limit

## PROTECTION

AC input fuse or optional breaker  
 DC output fuse or optional breaker  
 Automatic current limiting  
 AC surge suppressor  
 Slow start circuitry  
 Reverse battery protection

## VENTILATION

Natural convection cooling

## CABINETS

ANSI #61 light gray powder coat  
 14/18 guage steel  
 Wall or floor mounting

## STANDARD CONTROLS

Float/high rate switch for manual control

## STANDARD DISPLAYS

AC-ON LED  
 High rate charge LED  
 DC voltmeter and ammeter -2% accuracy

# MODELS

## W/STANDARD FILTER

OUTPUT CASE WT  
 VOLTS AMPS SIZE LBS

ABC11	-12	-3	W2	24
ABC11	-12	-6	W2	28
ABC11	-12	-10	W2	33
ABC11	-12	-15	W2	50
ABC11	-12	-20	W2	60
ABC11	-12	-25	W2	65
ABC11	-12	-30	W2	75
ABC11	-12	-40	W2	90
ABC11	-12	-50	W3	100
ABC11	-24	-3	W2	28
ABC11	-24	-6	W2	34
ABC11	-24	-10	W2	42
ABC11	-24	-15	W2	75
ABC11	-24	-20	W2	85
ABC11	-24	-25	W2	95
ABC11	-24	-30	W2	110
ABC11	-24	-40	W3	125
ABC11	-24	-50	W3	140
ABC11	-24	-60	W4	210
ABC11	-24	-75	W4	250
ABC11	-24	-100	G1	310

ABC11	-32	-3	W2	30
ABC11	-32	-6	W2	45
ABC11	-32	-10	W2	70
ABC11	-32	-15	W2	80
ABC11	-32	-20	W2	95
ABC11	-32	-25	W2	110
ABC11	-48	-3	W2	32
ABC11	-48	-6	W2	45
ABC11	-48	-10	W2	75
ABC11	-48	-15	W2	90
ABC11	-48	-20	W2	105
ABC11	-48	-25	W2	120
ABC11	-48	-30	W3	135
ABC11	-48	-40	W3	150
ABC11	-48	-50	W4	170
ABC11	-48	-75	G1	320
ABC11	-48	-100	G1	360

ABC11	-120	-3	W2	60
ABC11	-120	-6	W2	75
ABC11	-120	-10	W2	95
ABC11	-120	-15	W3	160
ABC11	-120	-20	W3	185
ABC11	-120	-25	W3	205
ABC11	-120	-30	G1	225
ABC11	-120	-35	G1	285
ABC11	-120	-40	G1	325
ABC11	-120	-50	G1	355
ABC11	-120	-60	G1	480
ABC11	-120	-75	G1	570
ABC11	-120	-100	G2	610

ABC11	-240	-3	W2	85
ABC11	-240	-6	W2	110
ABC11	-240	-10	W3	195
ABC11	-240	-15	W4	285
ABC11	-240	-20	G1	330
ABC11	-240	-25	G1	360

## W/EXTRA FILTER

OUTPUT CASE WT  
 VOLTS AMPS SIZE LBS

ABC12	-12	-3	W2	40
ABC12	-12	-6	W2	50
ABC12	-12	-10	W2	60
ABC12	-12	-15	W3	80
ABC12	-12	-20	W3	90
ABC12	-12	-25	W3	100
ABC12	-12	-30	W3	110
ABC12	-12	-40	W3	120
ABC12	-12	-50	W4	135
ABC12	-24	-3	W2	50
ABC12	-24	-6	W2	55
ABC12	-24	-10	W2	65
ABC12	-24	-15	W3	90
ABC12	-24	-20	W3	105
ABC12	-24	-25	W3	115
ABC12	-24	-30	W3	140
ABC12	-24	-40	W4	160
ABC12	-24	-50	W4	180
ABC12	-24	-60	W4	250
ABC12	-24	-75	G1	320
ABC12	-24	-100	G1	360

ABC12	-32	-3	W2	50
ABC12	-32	-6	W2	60
ABC12	-32	-10	W3	85
ABC12	-32	-15	W3	100
ABC12	-32	-20	W3	120
ABC12	-32	-25	W3	140
ABC12	-48	-3	W2	50
ABC12	-48	-6	W2	60
ABC12	-48	-10	W3	95
ABC12	-48	-15	W3	115
ABC12	-48	-20	W3	135
ABC12	-48	-25	W3	150
ABC12	-48	-30	W4	200
ABC12	-48	-40	W4	230
ABC12	-48	-50	W4	280
ABC12	-48	-75	G1	380
ABC12	-48	-100	G1	420

ABC12	-120	-3	W3	85
ABC12	-120	-6	W3	100
ABC12	-120	-10	W3	125
ABC12	-120	-15	W4	200
ABC12	-120	-20	W4	235
ABC12	-120	-25	W4	285
ABC12	-120	-30	G1	305
ABC12	-120	-35	G1	365
ABC12	-120	-40	G1	405
ABC12	-120	-50	G1	445
ABC12	-120	-60	G1	570
ABC12	-120	-75	G2	670
ABC12	-120	-100	G2	710

ABC12	-240	-3	W3	105
ABC12	-240	-6	W3	140
ABC12	-240	-10	W4	240
ABC12	-240	-15	G1	370
ABC12	-240	-20	G1	425
ABC12	-240	-25	G1	550

## DIMENSIONS

All dimensions in inches. Selection of  
 some accessories require larger cabinets.

CASE SIZE	W2	W3	W4	G1	G2
Height	19	28	36	40	53
Width	16	16	16	33	33
Depth	12	14	16	19	24

(Specifications subject to change without notice.)



American Battery Charging, Inc.  
 15272 Newsboy Circle  
 Huntington Beach, CA 92649  
[www.abc-chargers.com](http://www.abc-chargers.com)

**Phone Contacts**  
 Telephone: 714-477-1599  
 Fax: 714-896-9679