



Power StoneTM

Remote AC Power Controller Reset/Reboot Equipment by Phone



Benefits

- Saves Money - The Power Stone pays for itself with one saved service visit
- Reduces Downtime - One phone call can correct problem equipment in minutes
- Protects Equipment - Leave equipment "off" until needed. Reduces power consumption and hacker exposure
- Application Flexibility – Automatic and Manual operations for versatility in a variety of applications

Applications

Routers
DSL Modems
Automated Teller Machines
Internet Kiosks
Leased Telephone Systems
Network Equipment
Digital Video Recorders
Voicemail Systems
Equipment Under Service Warranty
Out-of-Band Network Management

Product Overview

Control electrical power on remote equipment by phone with The Power StoneTM from Multi-Link, Inc.

The Power Stone is a phone call-activated AC power controller used to reboot and power up/down remote equipment. Connect The Power Stone to on-site equipment and a phone line to gain complete power control anywhere you can place a phone call.

The Power Stone is the tool of choice for equipment support applications. There is no longer a need to send a repairman to a remote site when equipment requires little more than a power reset.

With a variety of operating modes, The Power Stone has the flexibility to handle virtually any remote power application. A user-defined security code provides customized protection for your application.

The Power Stone can turn on power to idle equipment as the situation demands. Data collection and telemetry equipment can remain off during idle time. Leaving equipment turned off until power is needed reduces electricity consumption and equipment wear.

Save time, travel and maintenance costs by eliminating service calls. Technicians can check current power, or if there has been a past power outage, from any telephone.

Features

FULLY PROGRAMMABLE

Control and program via touch tones. No software or drivers to install.

AUTOMATIC MODE

The Power Stone is automatically activated by an inbound call and executes user-defined power command.

MANUAL OVER-RIDE BUTTON

One touch for uninterrupted power.

120 VOLT, 15 AMP RATING

Tackles the most demanding power applications.

PROGRAMMABLE SECURITY

ACCESS CODES

User defined transfer codes provide security and control.

NON-VOLATILE MEMORY

Preserves programming in power outage.


RJ-11 INTERFACE

Easy to install.

REMOTE PROGRAMMING AND DIAGNOSTICS

Our tech support team is available toll-free to program The Power Stone over the phone.

ONE YEAR LIMITED WARRANTY



Application Flexibility

The Power Stone has the flexibility to tackle the most demanding remote applications. Select from Automatic or Manual operations.

Automatic Operation

The Power Stone will control power automatically upon detecting the rings from an inbound call. Choose “Rings-to-trip” or “Constant on/off” settings:

- Power on Call - The Power Stone supplies power during the call, then powers down two minutes after the call terminates.
- Reboot - Detecting a call, The Power Stone interrupts power for 15 seconds, then supplies power again.
- Toggle - With each incoming call, The Power Stone supplies or cuts power to the connected device.
- Constant Mode - The Power Stone ignores call activity, and stays “constant on” or “constant off” until you manually change operation.

Manual Operation

Call in to The Power Stone from any touch tone phone to manually control power or change automatic settings. Pass code protected.

Ask our technicians

Our staff of technicians is available to answer any questions you may have about programming or installation. We can even test and program your unit over the phone! We are available before and after the sale to ensure your satisfaction and optimal performance for your application.

TOLL FREE: 800.535.4651
International: +1 859.885.6363
techsupport@multi-link.net
sales@multi-link.net

TECHNICAL SPECIFICATIONS

Model Number	PST59102	Switching Manual	Key Pad 4 or 6 digit security code command (on/off)
Power	120 VAC plug in (60 Hz)	Manual Override	Push button (on/normal operation)
Switching Contact	120/12 VAC 15A with reset breaker 1800W, 600W incandescent.	Power and Relay Status	LED; Remote audible read-back
Interrupt Modes	Automatic on ring detection. Manual pick up with security code.	Ringer Equivalence	1.1 B
Switching Auto	Reboot (15 sec off, then on) Toggle (on or off) Power on call then off after hang up + 2 min.	Physical:	3.4" W x 1.8" D x 6" H, 1 lb

Multi-Link, Inc
 122 Dewey Drive | Nicholasville, KY | 40356 USA
 Sales and Tech Support 800.535.4651
 FAX 859.885.6619
www.multi-link.net

Copyright © 2009-2104 Multi-Link, Inc.
 The Power Stone™ is a trademark of Multi-Link, Inc.